

Non Touch Screen Z Line Models Z8 - EMV Restaurant Quick Reference Guide
For **SPIn** Secure Payment Integration







**** Note: Terminal Will Default at "POS ONLINE" Until Transaction is Initiated By POS System ****
These steps have been provided as a guide for assistance.

CHIP CARD SALE	SWIPED OR MANUAL CARD SALE	DEBIT SALE
<ol style="list-style-type: none"> ➊ Terminal "wakes up" & changes from POS Online ➋ Insert Chip Card ➌ Press OK to confirm Sale Amount ➍ Input TIP AMOUNT if prompted and press OK <ul style="list-style-type: none"> - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> ➊ Terminal "wakes up" & changes from POS Online ➋ Swipe OR Manually Enter Card # ➌ Press OK to confirm Sale Amount ➍ Input TIP AMOUNT if prompted and press OK <ul style="list-style-type: none"> - If AVS prompts, input AVS information - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> ➊ Terminal "wakes up" & changes from POS Online ➋ Insert Chip Card ➌ When prompted press F2 for YES ➍ Input PIN # on PIN Pad and press OK ➎ Press OK to confirm Sale Amount ➏ Input TIP AMOUNT if prompted and press OK <ul style="list-style-type: none"> - Terminal communicates with the Host - Receipts Print
VOID TRANSACTION	RETURN TRANSACTION	SETTLE THE OPEN BATCH
<ol style="list-style-type: none"> ➊ Terminal "wakes up" & changes from POS Online ➋ If prompted input Manager Password (1234 default) <ul style="list-style-type: none"> - Receipts Print 	<ol style="list-style-type: none"> ➊ Terminal "wakes up" & changes from POS Online ➋ If prompted input Manager Password (1234 default) ➌ Insert Chip Card ➍ Press OK to confirm Return Amount <ul style="list-style-type: none"> - When applicable input PIN and press OK - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> ➊ From the POS ONLINE Screen press F3 for Favorites ➋ Highlight SETTLE DAILY BATCH and press OK ➌ If prompted input Manager Password (1234 default) <ul style="list-style-type: none"> - Terminal communicates with the Host - Settle Report Prints

Non Touch Screen Z Line Models Z8 - EMV Restaurant Quick Reference Guide
For SPIn Secure Payment Integration



** Note: Terminal Will Default at **"POS ONLINE"** Until Transaction is Initiated By POS System **
These steps have been provided as a guide for assistance.

SPIN BYPASS	BATTERY INDICATOR (FOR MOBILE UNITS)	WI-FI ICON INDICATOR (FOR WI-FI ENABLED UNITS)
<p>** Use these steps to process a stand alone transaction initiated from the payment device INSTEAD of the POS system. (Ie: POS is down)</p> <ol style="list-style-type: none"> From the POS ONLINE screen press F3 Highlight the Turn SPIn Bypass On option and press OK. Terminal Displays "Credit I Sale, Enter Amount" You are now ready to process a stand along transaction at the terminal. 	 Indicates Full Battery  Battery low, needs charging <p>When battery is charging the battery icon will animate indicating charging is taking place.</p>	 Wi-Fi Not Connected  Wi-Fi Connected Successfully
PRINTING REPORTS	EDIT TIPS FROM TERMINAL	CALL ME FEATURE (MUST BE ENABLED)
<ol style="list-style-type: none"> From the POS ONLINE screen press OK Highlight REPORTS and press OK Highlight Desired Report Type and press OK Input Password (1234 Default) and press OK <p>- 4 Report Prints</p>	<ol style="list-style-type: none"> From the POS ONLINE screen press F3 Highlight Cr/Db Edit Tips and press OK Highlight Desired Edit Method and press OK <p>- 4 Add tip amount to desired transaction</p>	<ol style="list-style-type: none"> From the POS Online screen press F4 Select "CALL ME" and press OK The terminal sends notification to the help desk and you will receive a call back from a representative with assistance.

Non Touch Screen Z Line Models Z8 - EMV Retail Quick Reference Guide
For **SPI**n Secure Payment Integration







**** Note: Terminal Will Default at "POS ONLINE" Until Transaction is Initiated By POS System ****
These steps have been provided as a guide for assistance.

CHIP CARD SALE	SWIPED OR MANUAL CARD SALE	DEBIT SALE
<ol style="list-style-type: none"> 1 Terminal "wakes up" & changes from POS Online 2 Insert Chip Card 3 Press OK to confirm Sale Amount <ul style="list-style-type: none"> - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> 1 Terminal "wakes up" & changes from POS Online 2 Swipe OR Manually Enter Card # 3 Press OK to confirm Sale Amount <ul style="list-style-type: none"> - If AVS prompts, input AVS information - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> 1 Terminal "wakes up" & changes from POS Online 2 Insert Chip Card 3 When prompted press F2 for YES 4 Input PIN # on PIN Pad and press OK 5 Press OK to confirm Sale Amount <ul style="list-style-type: none"> - If AVS prompts, input AVS information - Terminal communicates with the Host - Receipts Print
VOID TRANSACTION	RETURN TRANSACTION	SETTLE THE OPEN BATCH
<ol style="list-style-type: none"> 1 Terminal "wakes up" & changes from POS Online 2 If prompted input Manager Password (1234 default) <ul style="list-style-type: none"> - Receipts Print 	<ol style="list-style-type: none"> 1 Terminal "wakes up" & changes from POS Online 2 If prompted input Manager Password (1234 default) 3 Insert Chip Card 4 Press OK to confirm Return Amount <ul style="list-style-type: none"> - When applicable input PIN and press OK - Terminal communicates with the Host - Receipts Print 	<ol style="list-style-type: none"> 1 From the POS ONLINE Screen press F3 for Favorites 2 Highlight SETTLE DAILY BATCH and press OK 3 If prompted input Manager Password (1234 default) <ul style="list-style-type: none"> - Terminal communicates with the Host - Settle Report Prints

Non Touch Screen Z Line Models Z8 - EMV Retail Quick Reference Guide
For SPIn Secure Payment Integration



**** Note: Terminal Will Default at "POS ONLINE" Until Transaction is Initiated By POS System ****
These steps have been provided as a guide for assistance.

SPIN BYPASS	BATTERY INDICATOR (FOR MOBILE UNITS)	WI-FI ICON INDICATOR (FOR WI-FI ENABLED UNITS)
<p>** Use these steps to process a stand alone transaction initiated from the payment device INSTEAD of the POS system. (Ie: POS is down)</p> <ol style="list-style-type: none"> 1 From the POS ONLINE screen press F3 2 Highlight the Turn SPIn Bypass On option and press OK. 3 Terminal Displays "Credit I Sale, Enter Amount" 4 You are now ready to process a stand along transaction at the terminal. 	<div style="display: flex; flex-direction: column; align-items: center;"> <div style="display: flex; align-items: center; margin-bottom: 10px;">  Indicates Full Battery </div> <div style="display: flex; align-items: center; margin-bottom: 10px;">  Battery low, needs charging </div> <p style="text-align: center;">When battery is charging the battery icon will animate indicating charging is taking place.</p> </div>	<div style="display: flex; flex-direction: column; align-items: center;"> <div style="display: flex; align-items: center; margin-bottom: 10px;">  Wi-Fi Not Connected </div> <div style="display: flex; align-items: center;">  Wi-Fi Connected Successfully </div> </div>
PRINTING REPORTS	REPRINT RECEIPT OPTION	CALL ME FEATURE (MUST BE ENABLED)
<ol style="list-style-type: none"> 1 From the POS ONLINE screen press OK 2 Highlight REPORTS and press OK 3 Highlight Desired Report Type and press OK 3 Input Password (1234 Default) and press OK - 4 Report Prints 	<ol style="list-style-type: none"> 1 From the POS Online screen press F3 2 Highlight REPRINT CR/DB RCPT and press OK 3 Input Password (1234 Default) and press OK 4 Highlight desired option(s) and press OK - 5 Receipt Prints 	<ol style="list-style-type: none"> 1 From the POS Online screen press F4 2 Select "CALL ME" and press OK 3 The terminal sends notification to the help desk and you will receive a call back from a representative with assistance.